

UNITED STATES PATENT APPLICATION
OF

Stanford W. Crane, Jr., Myoung-soo Jeon,

Charley Ogata, Ton Wang,

Andreas Cangellaris and Jose Schutt-Aine

FOR

SEMICONDUCTOR DIE PACKAGE HAVING
MESH POWER AND GROUND PLANES

[0001] This application claims the benefit of priority based on provisional Application No. 60/270,635, filed on February 23, 2001, and incorporated herein by reference.

BACKGROUND OF THE INVENTION

Field of the Invention

[0002] The present invention relates to a semiconductor die package having mesh power and ground planes and a method for manufacturing such a die package.

Description of the Related Art

[0003] A semiconductor die or chip is an electrical component on which a microcircuit is built. The microcircuits can be interconnected together on the printed circuit board to form larger electronic circuits for use in radios, televisions, compact disc players, and computers, to name just a few. Because the semiconductor die is fragile, it is encased in a semiconductor die package to protect it from the environment. If one were to look inside an electronic device, such as a computer, compact disc player, or cell phone, one would see one or more printed circuit boards on which semiconductor die packages are mounted and electrically interconnected.

[0004] The semiconductor die package includes a housing that holds the semiconductor die and conductive leads or pins that extend from the bottom or sides of the housing. The conductive leads are electrically connected to the semiconductor die within the housing. The outside ends of the leads are typically connected to conductive paths on the printed circuit board or plugged into

a socket on the printed circuit board. This secures the semiconductor die package to the printed circuit board and permits electrical signals to pass between the semiconductor die and other components on the printed circuit board.

[0005] The integrated circuits built on semiconductor dies are becoming increasingly powerful.

5 As processing power has increased, the number of inputs and outputs between semiconductor dies and other circuit components has increased as well and is expected to increase further. Die packages must provide a larger number of leads or pins without significantly increasing the size of the package. In addition, semiconductor devices are being designed with lower operating power voltages in order to reduce size and power consumption. Notwithstanding lower power consumption, thermal performance remains an important factor in package design. As the
10 operating power is lowered and device speeds increase, signal integrity has become increasingly important concern. For example, in device operation, fluctuations in power and ground voltages should be limited. Large fluctuations in power and ground are not only inefficient, but may cause erroneous operation and may even damage the integrated circuitry on the die. Moreover,
15 parasitic inductances should be reduced to facilitate high-speed operation. Accordingly, there is a need for packages that are inexpensive, that can accommodate a large number of inputs and outputs, and that can support high speed, low power operation.

SUMMARY OF THE INVENTION

[0006] The present invention has been made in view of the above circumstances and has as an object to provide an economical, compact die package having large number of inputs and outputs.

5 [0007] A further object is to provide an economical, compact die package and mating socket having large number of inputs and outputs that may mounted be to a substrate, such as a printed circuit board.

[0008] A further object is to provide a die package having stable power and ground planes.

10 [0009] A further object is to provide a die package having cost effective power and ground planes.

[0010] A further object is to provide a die package having easily configurable power and ground planes.

[0011] A further object to provide an economical die package having stable power and ground planes and a mating socket that may mounted be to a substrate, such as a printed circuit board.

15 [0012] A further object of the invention is to provide a sturdy and reliable die package having a large number of inputs and outputs and stable power and ground planes.

[0013] A further object of the invention is to provide an improved power and ground plane arrangement that may be used with a die package, with a mating socket, or with a substrate.

[0014] Additional objects and advantages of the invention will be set forth in part in the description which follows, and in part will be obvious from the description, or may be learned by practice of the invention. The objects and advantages of the invention will be realized and attained by means of the elements and combinations particularly pointed out in the appended
5 claims.

[0015] It is to be understood that both the foregoing general description and the following detailed description are exemplary and explanatory only and are not restrictive of the invention, as claimed.

10
BRIEF DESCRIPTION OF THE DRAWINGS

[0016] The accompanying drawings, which are incorporated in and constitute a part of this specification, illustrate embodiment(s) of the invention and together with the description, serve to explain the principles of the invention.

15 [0017] Figures 1 and 2 provide perspective views of an illustrative embodiment of a cluster grid array die package and mating socket in accordance with the present invention.

[0018] Figure 3 provides a perspective view of an illustrative embodiment of a cluster grid array die package in accordance with the present invention.

[0019] Figure 4 provides a view of an illustrative embodiment of a housing base of the cluster grid array die package without substrate in accordance with the present invention.

[0020] Figure 5 provides a view of an illustrative embodiment of power and ground planes in the housing base in accordance with the present invention.

[0021] Figures 6 and 7 provide views of an illustrative embodiment of the power and ground planes in the housing base in accordance with the present invention.

5 [0022] Figure 8 provides a perspective view of a further illustrative embodiment of power and ground planes in the housing base in accordance with the present invention.

[0023] Figures 9 and 10 provide side and bottom views, respectively, of the further illustrative embodiment of the power and ground planes in the housing base in accordance with the present invention.

10 [0024] Figure 11 provides a view of an illustrative embodiment of a mating socket in accordance with the present invention.

[0025] Figure 12 provides a view of an illustrative bottom view of the mating socket and printed circuit board pad or substrate layout to which the mating socket may be attached in accordance with the present invention.

15 [0026] Figure 13 provides a further illustrative bottom view of the mating socket in accordance with the present invention.

[0027] Figure 14 provides a further illustrative bottom view of the mating socket in accordance with the present invention.

[0028] Figure 15 shows an illustrative embodiment of a single buttress and cluster of package pins in accordance with the present invention.

[0029] Figure 16 shows a cross section of an illustrative embodiment of the die package of Figure 7.

5 [0030] Figures 17 and 18 show an illustrative electrical path between a die or substrate and a circuit board through a cluster grid array die package and mating socket.

[0031] Figures 19 and 20 show the mating of pin clusters of a cluster grid array die package and a mating socket according to an illustrative embodiment of the present invention.

10 [0032] Figure 21 illustrates an exemplary embodiment of a mating socket in accordance with the present invention.

[0033] Figure 22 illustrates a cutaway sectional view of the embodiment of Figure 22.

[0034] Figure 23 illustrates an exemplary embodiment of a die carrier in accordance with the present invention.

[0035] Figure 24 provides a cutaway sectional view of the embodiment of Figure 23.

15

DESCRIPTION OF THE PREFERRED EMBODIMENT

[0036] Reference will now be made in detail to the present exemplary embodiment(s) of the invention illustrated in the accompanying drawings. Wherever possible, the same reference numbers will be used throughout the drawings to refer to the same or like parts.

[0037] Figures 1 and 2 illustrate an exemplary embodiment of a cluster grid array semiconductor die package 100 and a mating socket 200 in accordance with the present invention. The die package 100 includes a housing 110 that houses at least one semiconductor die. As shown in Figure 2, a plurality of posts 120 extend from a bottom surface of the housing 110. Package pins 130 extend along the posts 120 and provide electrical paths from an interior to an exterior of housing 110. The mating socket 200 includes housing 210 having a plurality of sockets 220 in a top surface. A plurality of socket contacts or beams 230 are arranged within the sockets 200 as shown in Figure 1. The socket beams 230 include ends 232 that extend from a bottom surface of the housing 210. The ends 232 may be electrically connected to a printed circuit board (not shown) or other substrate, for example, by surface mounting, by plated through hole (PTH) technology, by press-fit, or by other suitable techniques. For example, if surface mounting were used, the ends 232 may be soldered to electrically-conductive pads on the surface of the substrate. As arrays become smaller, routing challenges escalate accordingly, especially in high speed, high pin-count devices. Electrical attributes are often the first to suffer. In high-density applications, particularly those involving pitches of 0.5 to 0.8 or less, the ends 232 may be surface mounted to pads at various levels within a multi-layer substrate, such as a printed circuit board, as described, for example, in U.S. Patent Nos. 5,543,586 and 5,659,953, to maintain a pluggable format.

[0038] The die package 100 mates with the mating socket 200 to form electrical paths between the at least one semiconductor die within the package housing 110 and the printed circuit board or substrate on which the mating socket 200 is mounted. Accordingly, electrical signals, power, and ground may be coupled to and from the at least one semiconductor die and the substrate.

5 [0039] In particular, the bottom surface of the package housing 110 is brought together with the upper surface of the mating housing 210 so that the posts 120 are received in the sockets 220. Consequently, as described in more detail below, the package pins 130 engage the socket contact beams 230 to form selectively attachable electrical connections. The package 100 is securely retained to the mating socket 200 by the force exerted between the socket contact beams 230 and the package pins 130 or by other suitable retention features. The die package 100 may be selectively detached from the mating socket 200 by pulling the die package 100 away from the mating socket 200, thereby slideably releasing the package pins 130 from the socket contact beams 230. Package 100 may be provided with, for example, 600-3000 package pins with arrayed pitches ranging from about 0.5 mm to 1.27 mm. A corresponding number of socket
10 contact beams 230 may be provided at corresponding pitches. Of course, these are merely examples and more (or fewer) pins may be provided at greater or smaller pitches.

[0040] For example, embodiments of the package may be designed to fit the existing and future needs of high pin-count flip chip devices. Larger arrays, such as 1 mm and 0.8 mm, may utilize a spreader substrate to fan out signals from the 0.25 mm and 0.5 mm pitches to a scale more

compatible with current cost-effective printed circuit board (PCB) technology. In many cases, 0.5 mm devices can be directly attached to the package structures. The packages may be designed to be near chip-scale in its smaller arrays. For example, 2500 inputs/outputs can be accommodated in a space approximately 32mm x 32mm. The packages 100 and mating sockets 200 are designed to provide the mechanical stability and rigidity necessary for true socket operation that provides sufficient stability to handle the rigors of real-world handling.

[0041] Figure 3 shows an illustrative embodiment of the package housing 110. As shown in Figure 3, the package housing 110 may include an upper lid 112 and a lower housing base 114. The upper lid 112 may be formed, for example, of a thermally conductive material, such as copper. As such, the upper lid 112 permits heat to be dissipated from the package housing 110. This permits semiconductor dies within housing 110 to operate more efficiently. Alternatively or in addition, the die(s) may be encapsulated within the lower housing base using a suitable encapsulant. The base 114 may be formed of an electrically-insulative material. The material may be selected to approximate the thermal expansion properties of the base material of the semiconductor die, such as silicon, germanium, gallium arsenide, etc. One suitable material for base 114 is liquid crystal polymer, such as Vectra E130I, which may be purchased from Ticona of Summit, NJ. Liquid crystal polymer material is highly accurate in molding operations, maintaining tight tolerances yet offering high flow during the injection step of the molding process. Vectra, in its various formulations, has the potential to be doped to deliver the desired

physical properties for an individual application, enhancing reliability and overall robustness. Of course, housing base 114 may be formed of another material or combination of materials as well.

[0042] As shown in Figure 3, for example, the housing base 114 include indentations 114a-114d.

As discussed further below, power contacts 166 and/or ground contacts 176 may be provided in one or more of indentations 114a-d. Of course, electrical paths for power and/or ground may be provided in other ways as well.

[0043] Figure 4 illustrates a top view of an exemplary embodiment of the housing base 114. As shown in Figure 4, the housing base 114 includes a floor 116 and walls 117 that define a cavity 118 in which one or more semiconductor dies may be held. The cavity 118 may also hold a substrate, such as a multi-layer ceramic or polymer substrate, upon which one or more semiconductor dies may be mounted. Such a substrate may be, for example, a spreader substrate that serves as an adapter for converting the pitch of signals of the die to a pitch compatible with a printed circuit board or other substrate to which the die carrier is mounted. Solder balls 150 may extend from an upper surface of floor 116. The solder balls 150 may be formed on the ends 132 of package pins 130. Of course, while solder balls 150 are described herein as an example, the solder balls 150 may be replaced, in whole or in part, with other electrical connection elements, such as pads or bumps, conductive paste or other conductive material or combination of materials, or simply the ends 132 of the package pins 130 themselves. The solder balls 150 may be provided in an array, for example, as shown in Figure 4. The solder balls 150 may be used to

form an electrical contact to the at least one semiconductor die or the substrate upon which one or more semiconductor dies are mounted. If a substrate is provided, the substrate may provide an electrical path from the solder balls 150 to landings on the upper surface of the substrate. The semiconductor die(s) may couple directly to the landings or via other electrical material, such as bonding wires, tape automated bonds, jumpers, or other suitable electrical coupling. The solder balls may be applied directly to the semiconductor die, either before or after dicing the wafer, and then mounted to the die carrier.

[0044] In an exemplary embodiment, a set of solder balls 150 may be used for power supply and another set of solder balls 150 may be used for ground. The remaining solder balls may be available for signal transmission and/or other purposes. In an exemplary embodiment, an outer ring 150-1 or ring portion of solder balls 150 may be used for power supply. Another ring of solder balls 150-2 just inside of the outer ring may be used for ground. The rest of the solder balls 150 may be used as signal paths or other purposes. In the example shown in Figure 4, 92 solder balls are used for power supply, 104 solder balls are used for ground, and 624 solder balls are available for signals or other purposes.

[0045] Figure 5 illustrates a section view of an embodiment of housing 110 taken through base 114 to show power planes 160 and ground planes 170 within the floor 116. Figure 5 shows ends 132 of package pins 130 extending through the floor 116 of the housing base 114. It should be noted that pairs of the package pins 130 may be used to provide power and ground connections.

As noted above, solder balls 150 may be formed on the ends 132 of the pins 130. The particular arrangement of power planes 160 and ground planes 170 shown in Figure 5 is merely exemplary. The power planes 160 and ground planes 170 may be formed as planar traces, as wirings, as frames, or another suitable shape.

5 [0046] The power plane 160 illustrated in Figure 5 is provided in four trace segments 161, 162, 163, and 164. Segments 161, 162, 163, and 164 extends along the periphery of floor 116 between indentations 114a and 114b, indentations 114b and 114c, indentations 114c and 114d, and indentations 114d and 114a, respectively. As shown, the segments 161-164 may be generally L-shaped. However, the segments of power plane 160 may be provided in other shapes, for example, C-shaped, or another suitable shape, or may be placed above or below each other. The segments 161-164 may be supplied with different supply power voltages, for example, if the die package housed multiple dies that operate with multiple power supply voltages. The power plane 160 may be provided by any number of segments, from a single segment to five or more segments.

15 [0047] Ground planes 170 may be formed by trace segments arranged in rows 171 and trace segments arranged in columns 172 to form a checkerboard pattern. The rows 171 and columns 172 pass between the ends 132 of package pins 130. The rows 171 and columns 172 may be spaced so as to pass between groups of one or more pins 130. As shown in Figure 5, for example, the rows 171 and columns 172 divide the pins 130 into groups of four. Figure 5 further

shows each of the rows 171 and columns 172 coupled together. However, this is not required.

The rows 171 and columns 172 may form multiple ground segments, for example, to isolate certain signal paths from others. For example, the checkerboard pattern shown in Figure 5 may be easily converted into two segments by cutting each row line 171 between two adjacent columns lines 172, into four quarter segments by further cutting each column line 172 between adjacent row lines 171, etc.

[0048] Power contacts 166 and ground contacts 176 may be provided at indentations 114a-114d.

Electrical connection between the power and ground planes 160, 170 and the mating socket 200 may be provided at power and ground contacts 166, 176. The embodiment shown in Figure 5 includes two power contacts 166 and two ground contacts 176 per indentation 114a-114d.

However, this is merely illustrative. Any number (1 or 3 or more) power and ground contact may be provided. The embodiment of Figure 5 shows four indentations 114a-114d, but it should be appreciated that 1, 2 (on either adjacent or opposite sides of housing 110), or more indentations 114 (e.g., multiple indentations on one or more sides of housing 110) may be provided. Moreover, the power and ground contacts 166, 176 need not be provided at indentations 114 at all. Power and ground contacts may be provided, for example, on the outer sides of housing base 114 or through the bottom surface of the housing base 114 (e.g., using package pins 130 or otherwise).

[0049] Figure 6 provides a cutaway view of a section of base 114 to illustrate one exemplary embodiment for forming contacts 166 and 176. Figure 7 illustrates the entirety of the embodiment shown in Figure 6. As best seen in Figure 6, the power plane segment 162 may extend along the base 114 at indentation 114b (not shown) to provide a power contact 166.

5 Similarly, power plane segment 161 may form a power contact 166. Ground plane 170 may include one or more extensions, such as extensions shown in Figure 6, that extend laterally along the outer side wall 117 at indentation 114b to form one or more ground contacts 176.

[0050] The power and ground contacts 166, 176 may contact power and ground mating pins 240 of mating socket 200 to form an electrical connection. The power and ground mating pins 240 may have a resiliently flexible contact beam 244 that flexes outwardly when in contact with the power and ground contacts 166, 176 to maintain a normal force for good electrical contact.

[0051] Figure 6 further illustrates holes 116a in floor 116 in which solder balls 150 sit. The holes 116a may extend entirely through the housing base 114 to accommodate package pins 130. Holes 116a to the power plane 160 and ground plane 170 do not necessarily extend through housing base 114, but may terminate at the power and ground planes 160, 170. As shown in Figure 4, such holes 116a enable the solder balls 150 to contact the power and ground planes 160, 170 to form an electrical connection.

[0052] Figure 7 provides an exploded view of an illustrative embodiment of the die package 100 to show the electrical contacts. A semiconductor die 300 and a substrate 310 are received in the

cavity 118 of the housing base 114. The semiconductor die 310 mounts to the substrate 310. The substrate 310 may be a multi-layer ceramic or polymer substrate that provides electrical connection between the solder balls 150 and the semiconductor die 300. Such a substrate 310 may be, for example, a spreader substrate that serves as an adapter for converting the pitch of signals of the die to a pitch compatible with a printed circuit board or other substrate to which the die carrier is mounted. The substrate 310 contacts the solder balls 150 exposed on the floor 116 of the base 114. Some of the solder balls 150 contact the package pins 130 and others contact the power and ground planes 160, 170. The lid 112 seals to the base 114 to retain the die 300. The die package 100 couples to the mating socket 200 such that package pins 130 engage socket contact beams 230 and such that power and ground contacts 166, 176 engage power and ground mating pins 240. Ends 232 of the socket contact beams 230 (not shown) and ends 242 of mating pins 240 (not shown) may couple to a substrate, such as a printed circuit board.

[0053] Because package electrical performance is a factor for GHz-bandwidth signal transmission and sub-nanosecond switching, interconnect impedance control through the package is important for suppressing reflections and attendant noise interactions at the higher end of the signal spectrum. Maintaining good impedance control in a structure as three-dimensional as a high-density package is a challenging undertaking, requiring careful consideration of how power and ground distribution is effected through the package. In other words, in addition to designing the power and ground distribution for reducing inductance during switching, attention must be

paid to providing an effective return path for the current for all signal traces in the package. This purpose contributed to the introduction of power/ground planes in high-speed packages.

[0054] Figures 8-10 illustrate an example of an alternative power and ground mesh combination used on the chip side in the package housing. As in Figures 5-7, the power/ground planes may be positioned directly under the die or die/substrate combination to assist in power distribution and signal termination. As shown in Figures 8-10, ground plane 170 may be provided at a first level within the floor 116 of package 100 and the power plane 160 may be provided at a second level within the floor 116. For example, the power and/ground planes may be insert molded into the floor of package 100 or attached with an adhesive after the floor, or a portion of the floor, is molded. In the latter case, the power and ground planes 160, 170 may be combined into a separate unit. As shown in Figures 8-10, the ground plane 170 is provided between the power plane 160 and the intended location of the die 300. Of course, as an alternative, the location of the power plane 160 and the ground plane 170 may be reversed. A coating may be applied to one or both of the power and ground planes 160, 170 to electrically insulate them from each other and other components. The coating(s) may be extremely thin to reduce inductance, e.g., of the package. The ground plane 170 may have a grid design of interconnecting rows 171 and columns 172. As above, a plurality of solder balls 150 may be used to couple the ground plane 170 to the semiconductor die 300 or to the substrate 310, for example.

[0055] The power plane 160 may also have a grid design of intersecting rows 165 and columns 167. The power plane 160 is designed to have a greater overall length and/or width than the ground plane 170 to improve electrical performance and to simplify electrical connection to solder balls. Of course, other arrangements are possible. In the embodiment shown in Figures 8-10, the power plane 160 includes a central row 165 and a central column 167 that intersect at a center plane 168. Of course, additional rows 165 and columns 167 may be provided if desired.

[0056] Power plane 160 is coupled to solder balls 150 by plugs or extensions 169 that extend through a hole 116a (not shown) in base 114. In the example illustrated in Figures 8-10, extensions 169 are provided spaced apart at the periphery of power plane 160. This arrangement provides additional space for pins 130 and/or signal pin extensions 131, which may be used to connect the signal pins to the solder balls 150, to the die, or to the substrate. Signal pin plugs or extensions 131 may be formed by two parts: a vertical extension 131a and a horizontal extension 131b. Vertical extensions 131a provide a vertical path toward the die 300. Horizontal extensions 131b may be used to fan out the signal paths between the die 300 and the package pins 130. Extensions 169 are also provided at the center plane 168 to permit connection to solder balls. Figures 8 and 10 illustrate four extensions 169 providing electrical connection from the center plane 168 to the solder balls 150. Of course, additional extensions 169 may be provided between the power plane 160 and the solder balls 150. Alternatively, extensions 169 may provide electrical contact to the die 300 or to the substrate 310 on which the die is mounted.

[0057] It should be pointed out that for the sake of clarity, the metallization density in the planes 160, 170 shown in Figure 8-10 does not reflect the actual metallization density. For example, in the case of a 0.8 mm-pitch package design with 624 signal pins, the number of “cells” in the ground mesh 170 may be 156 and the number of corresponding power cells in the power mesh 160 may be 36. In the mesh structure, the area array contact with the die is facilitated for both power and ground with the chip. Furthermore, the arrangement is such that the “effective” value of the power and ground inductance introduced by the package remains low. Even though the quantification of an “effective” value of the power inductance during switching is difficult, an approximate calculation of such a quantity is possible by considering in a qualitative manner those factors that have an impact on its value. For an example having a 0.8 mm pitch, the calculated value of the self-partial-inductance of the ground mesh is 0.32 nH. Additionally, the mutual partial-inductance between the power and ground mesh in the case of a 0.3 mm separation between them is found to be 0.2 nH. Thus, the effective value of ground inductance introduced by the ground mesh during switching is 0.12 nH in this example.

[0058] A similar calculation can be performed to estimate the worst-case effective inductance introduced by the power mesh 160. Assuming the example provided above and that the power mesh metallization is the same as that of the ground mesh, the worst-case effective inductance introduced by the power mesh is found to be 0.23 nH. This value is higher than that of the ground mesh because of the coarser mesh metallization used for the power mesh. Remarkably,

this value can be reduced even further by increasing the width and thickness of the metallization.

In any case, it is stressed once more that these are worst-case values for specific examples, and that the power-ground mesh configuration is designed in such a manner that the “effective value” of power and ground inductance can be controlled through the assignment of some of the pins in the clusters as extra power and ground pins.

[0059] The presence of the ground plane in the package housing immediately beneath the die likewise allows for impedance control for those signal traces that need to be fanned out away from the die. The mesh structure can be added in one or more places, depending upon the electrical needs. For example, in the case of a 0.8 mm-pitch package design, signal trace impedance values in the range of 50 to 70 Ohm are easily attainable through selection of signal trace width and separation from the ground mesh. The same holds true for signal traces routed between the power and ground mesh planes, as well as below the power mesh plane. The number of signal layers that may be used is dependent on input/output pin count and density, as well as crosstalk constraints.

[0060] Figure 11 illustrates an exemplary embodiment of a mating socket 200. As shown, mating socket 200 includes a housing 210 having a floor 216 and side walls 217 that define a cavity 218 sized to receive the die package 100. The floor 216 includes a plurality of sockets 220. Sockets 220 are sized and positioned to receive the posts 120 of the die package 100. Sockets 220 may be arranged in an array pattern. Socket contact beams 230 are positioned

within the sockets 220. In the example shown in Figure 11, four socket contact beams 230 are provided for each socket 220. However, any number of socket contact beams 230 may be provided per socket, such as 2, 3, or 5 or more. The socket contact beams 230 extend through and are held in the housing 210. For example, the housing 210 may include holes formed therethrough into which socket contact beams 230 are inserted and held via friction, adhesives, and/or mechanical expedients, such as spurs, wedge, or tongue-and-groove arrangements. Power and ground mating pins 240 may be similarly held in the housing 210. The embodiment of Figure 11 includes a cam mechanism 250 with a cam lever 252. The cam mechanism 250 may be used, as described in more detail below, to reduce the insertion force needed to plug the die package 100 into the mating socket 200.

[0061] Figure 12 illustrates a bottom surface of mating socket 200 and a portion of a substrate, in this case a printed circuit board 400, to which it may be attached. Ends 232 of socket contact beams 230 and ends 242 of mating pins 240 extend from a bottom surface of housing 210. The ends 232, 242 may contact pads 410 formed on circuit board 400 to form an electrical connection. In particular, the ends 232, 242 may be soldered to the pads 410 to retain the mating socket 200 to the circuit board 400 and at the same time form an electrical connection. As shown, the pads 410 are arranged in the same pattern as the ends 232, 242. Traces (not shown) may lead to contact pads 410 to couple electrical signals to and from the contact pads. Alternatively, the pads 410 may be replaced by plated through holes through which the ends 232, 242 may extend.

Solder may be used to electrically connect and retain ends 232, 242 in such through holes. Of course, the description herein is merely exemplary and other techniques may be used to couple the mating socket 200 to a substrate.

[0062] Figures 13 and 14 illustrate two alternative arrangements of the bottom surface of mating socket 200. For simplicity, Figures 13 and 14 illustrate only the ends 232 of socket contact beams 230. Figures 13 and 14 each illustrate designs incorporating a ground mesh 260. In particular, Figure 13 shows the bottom surface of mating socket 200 with an isolation gate structure providing a ground for signal beams 230. A reduced number of beams 232 is shown for the sake of clarity. More particularly, the ground mesh 260 includes electrically-conductive rows 261 and columns 262 that intersect to divide the ends 232 of beams 230 into groups or cells.

While Figure 13 illustrates a ground mesh 260 that divides the ends 232 of beams 230 into cells of four, the mesh 260 may be designed to divide the ends into groups of one, two or three, or five or more. The rows and columns 261 and 262 include bumps 265 for making electrical contact with the substrate, e.g., printed circuit board, on which the mating socket 200 is mounted.

Bumps 265 are spaced periodically on the surface of the ground mesh 260. Of course, bumps 265 may be omitted or replaced by other contact structure.

[0063] An alternative grounding structure, as shown in Figure 14, features isolation rows 261, allowing for somewhat lower manufacturing costs as well as improved airflow beneath the socket 200. As shown in Figure 14, the rows 261 are provided between every other row of ends

232 of beams 230. As above, rows 216 may be provided between every row of ends 232 or between a larger number of rows. In Figures 13 and 14, the meshes 260 are regularly spaced, but of course irregular mesh spacing may be used if desired.

[0064] As mentioned earlier, in addition to the use of the power mesh and the peripheral ground pins, the beams 230 in the cluster or group may also be used for a more direct power distribution to different locations on the die 300. The presence of the ground structure 260 facilitates the reduction of the effective power inductance that the beams 230 present during switching. As a measure of this inductance value, let us consider the case in which four beams 230 in one cluster are used as power pins. In a 0.8 mm-pitch design, where the stacking height is 7.6 mm, and a socket ground structure as detailed in Figure 14, the “effective” power inductance during switching is calculated to be 0.23 nH. This value can be further reduced through the assignment of more of the beams as power elements.

[0065] Figure 15 illustrates an example of a post 120 and package pins 130 that may be used in connection with the present invention. Post 120 extends from a lower surface of housing base 114. In one preferred embodiment, the posts 120 are formed simultaneously with the housing base 114 using a molding process. The post 120 may include axially-extending grooves 122 spaces around the circumference of the post 120. The grooves 122 are adapter to receive at least a portion of package pins 130. The post 120 may have a generally circular cross section with cut-outs for grooves 122. However, other cross-sectional shapes are possible as well, such as

squares, rectangles, pentagons, hexagons, etc., with or without grooves 122. Post 120 further includes an angled tip 124. The tip 124 aids insertion of the post 120 into a socket 220 of the mating socket 200. The tip 124 may, for example, help to properly spread socket contact beams 230 in the event of minor misalignment.

5 [0066] Package pins 130 include an end portion 132 (not shown in Figure 15), a stabilizer portion 133 extending within the housing, contact portion 134 extending outside of housing 110. The stabilizer portion 133 functions to hold the pin 130 stable in the housing and may be thicker than the contact portion 134. The contact portion 134 is adapted to form an electrical connection with socket contact beams 230. The contact portion 134 may extend in groove 122. The contact portion 134 may include a rounded tip 136. The rounded tip 136 helps to flex socket pin 130 outwardly during mating. In the example of Figure 10, four package pins 130 are provided per post 120. However, another ratio of pins 130 per post 120 may be used, such as 2, 3, or 5 or more.

[0067] Figure 16 illustrates an exemplary cross section of die package 100 through posts 120.

15 Posts 120 extend from the bottom surface of housing base 114. Package pins 130 extend through the housing base 114 and along the posts 120 such that a contact portion 134 is exposed externally of the package housing 110. The stabilizer portion 133 of each package pin 130 is held within the housing base 114, for example, by friction, an adhesive, spurs, and/or other suitable expedients. The portion 133 may be thicker than the contact portion 134 to provide

added stability. Ends 132 of package pins 130 contact solder balls 150, which contact substrate 310 through holes 116a in floor 116. Holes 116a also permit solder balls 150 form contacts between power plane 160 and substrate 310 and between ground plane 170 and substrate 310.

As shown in Figure 16, the rows 171 and columns 172 of ground plane 170 extend between the

5 package pins 130. Substrate 310 may have multiple levels and vias that form electrical connections between its bottom surface, which contacts the solder balls 150 and its upper surface adjacent die 300. Substrate 310 may make direct electrical connections with die 300.

Alternatively or in addition, substrate 310 may have bonding pads which electrically couple to the die 300 via electrically conductive material, such as wire bonds, tape automated bonding, jumpers, etc. Thermal lid 112 caps the housing base 114 to retain and protect die 300.

10 [0068] As noted above, the base 114 may be formed by molding from a polymer, such as a liquid crystal polymer. Holes 116a may be formed during the molding process or by removing material after molding. The electrically-conductive power and ground planes 160, 170 may be a frame, such as a lead frame, that is molded into the base 114 when the base 114 is formed or may be applied to a surface of the base 114 after the base is molded. In such a case, an additional floor piece 116 having holes 116a may be formed over the power and ground planes 160, 170.

15 Package pins 130 may be cut from wire stock and machined to the shape shown in the Figures, for example. The package pins 130 may be inserted into the holes 116a from the direction of the cavity 118. If a two-piece base and floor is used, the pins 130 may be inserted before the floor

116 is applied. In such a case, it is important that the ends 132 of pins 130 register with holes 116a. Solder balls 150 are laid over the holes 116a to contact the ends 132 of pins 130, the power plane 160, and the ground plane 170. The substrate 310 (if used) and die(s) 300 are then laid over the solder balls 150. Solder balls 150 may be melted to form an electrical and mechanical attachment and any other electrical connection within the cavity 118 may be made (e.g., wire bonding, etc.). The lid 112 may then be sealed to the base 114 to complete the package 100.

[0069] As shown in Figure 16, the lengths of the contact portions 134 of package pins 130 may vary. For example, the length of the contact portion 134 of pin 130-1 is greater than the length of the contact portion 134 of pin 130-2. As a result, the contact portions 134 of pins 130-1 and 130-2 engage the corresponding contact beams 234 of the mating socket at different times during mating. In this way, the insertion force needed to couple the package 100 with the mating socket 200 may be reduced.

[0070] Figures 17 and 18 illustrate an exploded view of an exemplary electrical connection path between die 300 (or substrate 310) and a substrate 400, such as a printed circuit board, for a single cluster of package pins 130 and socket contact beams 230. The signal paths through the package 100 and the socket 200 are realized through the four-pin cluster shown in Figures 17 and 18. Die 300 couples to solder balls 150, which are in electrical contact with the ends 132 of package pins 130. As noted above, extensions or plugs 131 may be provided to couple the ends

132 of pins 130 to the solder balls 150 or directly to the die 300 or substrate 310. Contact portions 134 of package pins 130 extend along the post 120 and are spaced apart around the circumference of the post 120. The post 120 and package pins 130 are received in a socket 220 (not shown for ease of understanding) and engage socket contact beams 230.

5 [0071] The socket contact beams 230 include resilient, flexible contact beams 234 that extend from the housing 210. Contact beams 234 each include an upstanding portion 235, a first angled portion 236, and a second angled portion 237. The first angled portion 236 angles inwardly, toward the space for receiving post 120. The second angled portion 237 angles outwardly away from the space for receiving post 120. Accordingly, as the post 120 is received, the second angled portion 237 helps to spread the contact beam 234 outward away from the post 120. The first angled portion 236 helps to provide a normal force against the contact portion 134 of the package pins 130 for a good electrical connection. The socket contact beams 230 further include a stabilizer portion 233 held within the housing 210, for example, by friction, adhesive, spurs, tongue-and-groove, wedge, and/or other expedients. The stabilizer portion 233 may be thicker than ends 232 and beam 234 to maintain stability of the pin 230. Ends 232 of socket contact beams 230 extend from a bottom surface of housing 210 and may be surface mounted, for example, to bonding pads 410 on substrate 400. Accordingly, as provided in this example, an electrical path is formed from the die 300, to the solder balls 150, to the package pins 130, to the socket contact beams, and to the substrate 400.

[0072] The socket housing 210 may be formed by molding, for example. Similar to the package housing, the socket housing 210 may be molded from a polymer material and, after molding, the socket contact beams 230 may be inserted. Alternatively, the socket housing 210 may be molded around the contact beams 230. In addition, a ground or shield structure may be added to the socket housing 210. For example, the ground or shield may be molded into the socket housing 210.

[0073] Figures 19 and 20 illustrate an embodiment in which insertion of the posts 120 into the socket 220 is aided by cam 250. As noted above, the contact beams are designed to have an adequate normal force to maintain positive contact under a variety of conditions and in numerous product applications. Typically, along with a substantial normal force of the contact beam comes a correspondent increase in insertion force. Although not objectionable on a per-contact beam basis, in a high pin-count configuration the insertion force may become problematic. To afford both high reliability and a high pin-count form, zero insertion force (ZIF) or low insertion force (LIF) options may be supported. In Figures 19 and 20, the beams 230 are “cammed” open to provide either zero- or very low-insertion force.

[0074] As shown in Figures 19 and 20, a cam 250 may be positioned between a cluster of socket contact beams 230. Cam 250 is movable along the socket contact beams 230 between at least two positions. In a first position, as shown in Figure 19, cam 250 engages ridges 238 formed on surfaces of beams 234 of socket contact beams 230. The ridges 238 may be wedge shaped, for

example. As cam 250 is moved along beams 234 of the socket pin cluster, it engages and slides along ridges 238, thereby causing the beams to flex outwardly. Moreover, the sliding interaction of the cam 250 on the surface of beams 234 provides a significant wiping action to further assure good electrical contact. In a second position, as shown in Figure 20, the cam 250 is located adjacent the housing 210 and does not engage ridges 238. Consequently, cam 250 does not flex beams 234 outward. Rather, the beam 234 resiliently returns to a substantially unflexed position.

[0075] The cam mechanism 250 may be used to reduce the insertion force required to mate the package 100 with the mating socket 200. For example, the cam 250 may be placed in the first position to spread the socket contact beams 230 prior to mating with the package pins 130, as shown in Figure 19. Once the package pins 130 are placed in position within the cluster of socket contact beams 230, the cam 250 may be moved to the second position, thereby permitting the socket contact beams 230 to collapse upon the package pins 130 to form electrical connections. Note that, in accordance with this embodiment, it is not necessary for the post 120 to contact the cam 250. Cam 250 may be moved using externally applied pressure, either by man or machine, to a cam lever 252, shown in Figures 11 and 12, for example.

[0076] The semiconductor die packages according to the present invention take into account electrical, mechanical, and thermal design considerations to provide the signal integrity useful for present-day semiconductors. Electrical performance considerations are important in the package design as next-generation application-specific integrated circuits (ASICs) and high-end

processors are pushing the input/output frequencies toward the microwave frequency band. To support such bandwidths without excessive noise generation and signal degradation, the signal transmission and power distribution through the package parallel those used for microwave signal transmission, yet at densities more than two orders of magnitude greater. In particular, the present package designs both eliminate parasitic inductance in the power distribution network and facilitate satisfactory impedance control through the package.

[0077] With regard to cost, the package designs described herein exhibit good material efficiency due to highly dense structure and high material utilization per I/O. Processing costs of assembling the various components of the package product family are low due to the straightforward assembly process and the redundant nature of the cluster structures. The designs permit fully automated assembly. Moreover, the pluggable aspect of the designs advantageously enable population of the most expensive components during the final assembly phase, thereby reducing work in process and lowering inventory costs.

[0078] The power and ground planes described herein may be provided in any position of the assembly. The power and ground arrangements described herein and shown, for example, in Figures 5-10, may be used in other semiconductor die carriers, such as flip chip carriers, ball grid arrays, etc., may be integrated into the mating socket, or may be used in printed circuit boards or other substrates (such as ceramic laminate, organic laminate, or silicon substrate, for example), to improve electrical performance. The power and ground planes may be provided, for example,

above a substrate, as part of the substrate, below a substrate, as part of the die carrier, as part of the mating socket, or any combination of the above. As noted above, the power and/or ground planes 160, 170 may have a coating that electrically insulates them. The coating may be extremely thin to reduce inductance. For example, the power and ground planes may be applied to a mold and encapsulated so as to become part of the die carrier 100 or mating socket 200.

Further, the thickness of the ground and power planes may be altered by stacking additional layers. For example, a stacked ground/power/ground structure or a stacked power/ground/power structure may be provided. In general, these power and ground planes may run perpendicular to the signal pins, however, this is not required.

[0079] Figures 21 and 22 illustrate an exemplary embodiment of a mating connector 200 in accordance with the present invention. The mating connector 200 of Figures 21 and 22 include many of the features and properties of the embodiment shown in Figures 1 and 2, for example, and described above. In general, the mating connector 200 includes a housing 210 having a plurality of sockets 220 and a plurality of electrically-conductive socket beams 230 arranged in the sockets 230. Housing 210 may include a floor portion 216 through which the sockets 220 are provided and walls 217. Ends 232 of socket beams 230 (not shown in Figure 21) extend from a bottom surface of the housing 210 for electrical connection to a substrate, such as a printed circuit board. As shown in Figures 21 and 22, sockets 220 may have a square shape, for example, but other shapes, e.g., circles, ovals, or polygonal shapes, are possible as well. Mating

connector 200 further includes power and ground mating pins 240 having resiliently flexible contact beams 244 that flex outwardly when on contact with the power and ground mating contacts 166 during mating between the die carrier and mating socket 200. Power and ground mating pins 240 may be provided in individual passages 212 formed in housing 210. The passages 212 may be provided, at least partially, in walls 217. As shown in Figure 21, the power and ground mating pins 240 may be provided on opposite sides of housing 200. Of course, the power and ground mating pins 240 may be provided on adjacent sides, on one side only, on three or four sides, or elsewhere.

[0080] As shown in more detail in Figure 22, floor 216 may comprise a first insulative layer 216-1, a ground mesh 270, and a second insulative layer 216-2. The floor 216 includes holes 216a that at least partially define sockets 220 and through which the posts 120 and package pins 130 of the die carrier may be inserted. As noted above, the ground mesh 270 may have a thin coating that insulates the ground mesh 270, including for example on the surfaces that define the holes 216a. Of course, the structure between the first and second insulative layers 216-1 and 216-2 may be a power plane, a combination of adjacent power and ground planes, or a stack of a one or more power and ground planes, as discussed above. Housing 210 includes a base 214 on which the floor 216 may be mounted. A cavity 218 may be defined between the base 214 and the floor 216. At least the flexible contact beams 234 of the socket beams 230 may be provided, or extend through, the cavity 218. Accordingly, at least during mating of the die package 100 and the

mating socket 200, the package pins 130 and/or the socket beams 230 will pass through the ground mesh 270. Stabilizer portions 233 of the socket beams may be retained in the base 214, for example, by friction, adhesives, and/or mechanical expedients as noted above. Mating socket 200 of Figures 21 and 22 may additionally include other features noted above in connection with the other Figures, but for brevity have not been repeated here.

[0081] The mating socket 200 of Figures 21 and 22 may be easily manufactured. For example, the base 214 may be molded, e.g., from a liquid crystal polymer material such as VECTRA™. Beams 230 and 240 may be inserted into the molded base 214, or molded into the base 214. Floor 216 may be formed separately and attached to the base 214.

[0082] Figures 23 and 24 illustrate a further exemplary embodiment of a die package 100 in accordance with the present invention. As shown in Figures 23 and 24, the die package 100 is generally similar to that shown in Figures 1 and 2, for example, and includes many of the same structures and features. As above, the die package 100 includes a housing 110, a posts 120 extending from a bottom surface of housing 110, and package pins 130 extending along the posts 120 as shown in Figure 24, for example.

[0083] Housing 110 includes a base 114 having a floor 116 and walls 117. The floor 116 and walls 117 define a cavity in which one or more semiconductor dies may be housed. The die(s) may be enclosed within the base 114 with a lid (not shown) and/or encapsulant, as described above. Power contacts 166 and/or ground contacts 176 may be provided at the periphery of base

114. As shown in Figure 23, the power contacts 166 and ground contacts 176 may be provided on opposite sides of the base 114. As such, the die package 100 may be mated with the mating socket of Figures 21 and 22. Of course, as noted above, power and/or ground contacts may be provided on one side, on two adjacent sides, on three or more sides of base 114, elsewhere.

5 [0084] Power plane 160 and ground plane 170 are provided within floor 116. Power plane 160 and ground plane 170 are separated by insulative material. Power plane 160 includes a grid of intersecting rows 165 and columns 167. Extensions 169 of power plane 160 provide access to the surface of floor 116. Ground plane 170 includes a grid design of intersecting rows 171 and columns 172. Ends 132 of package pins 130 are exposed at the surface of floor 116 so that
10 groups of one or more ends 132 (four in the example of Figures 23 and 24) are provided between the rows 171 and columns 172. Extensions (not shown) couple the power plane 160 to the power contacts 166. Likewise, extensions (not shown) couple the ground plane 170 to the ground contacts 176. Die package 100 of Figures 23 and 24 may additionally include other features noted above in connection with the other Figures, but for brevity have not been repeated here.

15 [0085] It should be borne in mind that the particular embodiments of the present invention are but possible solutions to the complex problem of addressing thermal/mechanical and reliability constraints without sacrificing electrical performance. The flexibility of the design features described herein allows for a wide range of solutions that may vary with individual applications. Additionally, the pluggable alternative now affords systems architects fresh opportunities to

partition their products so as to provide new levels of sophistication in systems employing high pin-count devices.

[0086] Other embodiments of the invention will be apparent to those skilled in the art from consideration of the specification and practice of the invention disclosed herein. It is intended

5 that the specification and examples be considered as exemplary only, with a true scope and spirit of the invention being indicated by the following claims.

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
221